# BlueDriver-F3<sup>™</sup> <sup>®</sup>

Wireless Audio Interface

7 kHz HD VOICE



FEATURES	D3	F3	МЗ
» HD Voice (Wide-Band Speech)	•	•	•
» 3-pin Female XLR Input	•	•	
» 3-pin Male XLR Output	•		•
» 3.5 mm Input	•		•
» 3.5 mm Output	•	•	
» 3.5mm Earpiece/Headphone Output		•	
» Trim Pot Adjusts Mic Level		•	
» Headset/Phone Switch		•	•
» Mini USB Power Jack		•	٠
<ul> <li>» &gt; 18 Hours on one</li> <li>9-volt Alkaline Battery</li> </ul>	•		
» >6 hours on Internal Li-Ion Battery		•	٠

BlueDriver-M3 and Daptor Three shown for comparison.

D3 =Daptor Three F3 = BlueDriver-F3 M3 = BlueDriver-M3

#### Mic or Mixer output to your Bluetooth Device.

Pair to your Bluetooth enabled phone, headset, or speaker to route audio through your Bluetooth device. New to BlueDriver-F3, the 3.5 mm stereo output jack is now a headphone output jack, allowing you to monitor the return signal from your Bluetooth device over wired ear buds or headphones.

### Headset Mode vs. Phone Mode

A switch selects between connection to a Bluetooth headset or speaker, or to a phone.

### **Headset Connect:**

Pair BlueDriver-F3 to your Bluetooth headset or speaker. BlueDriver-F3 functions like a phone to send and receive audio from a Bluetooth wireless headset, or transmit audio to a Bluetooth wireless speaker.

#### Phone Connect:

Pair BlueDriver-F3 to your phone to capture wireless Audio-for-Video, make a live call into the station, or bring caller audio into your live event or podcast.



© 2018, JK Audio, Inc. 1311 E. 6th St. Sandwich, IL. 60548 800.552.8346 • 815.786.2929 Se Habla Español

jkaudio.com info@jkaudio.com



# BlueDriver-F3<sup>™</sup> <sup>8</sup>

Wireless Audio Interface

7 kHz HD<u>Voice</u>





## Wireless Audio for Smartphone Video

BlueDriver-F3 along with a professional video camera app, lets you record broadcast worthy interviews while placing the mic in the subjects hand for improved audio guality.




# **Backup Audio Path for Remote Broadcasts**

You may have the finest IP CODEC available, but if the internet goes down, there goes the remote.



#### Live Man-On-The-Street Interviews

Broadcast high quality phone interviews using your favorite mic and headphones.



### **Transmit Bluetooth A2DP Audio**

The "Headset" mode of BlueDriver-F3 connects to Bluetooth headphones or wireless speakers, and provides full 20 kHz audio bandwidth A2DP audio.

### **SPECIFICATIONS**

Input	
3-pin Female XLR:	1k ohms / -34 dBu nom.
Output	
1/8" (3.5mm) Stereo:	16 ohms / 35 mW (750 mVRMS)
Misc.	
Battery:	250 mAh Internal Lithium-Ion Polymer Rechargeable Battery with a Mini-USB Charging Port
Size:	1.1" x 4.4" (2.8 cm x 11.2 cm)
Weight:	2.1 oz. (60 grams)

#### Bluetooth Wireless Technology

Standard:	3.0	
Frequency Response:	Hands-Free (Full Duplex): 300 Hz– 3.4 kHz Hands-Free (Full Duplex HD): 50 Hz– 7 kHz A2DP (Master » Headset): 30 Hz–17 kHz	
End-to-End Latency:	Audio-for-Video or Audio Recording: 25 ms using HD Voice Profile. Streaming Full Bandwidth Audio: 150 ms using Bluetooth A2DP Profile.	
Range:	66 ft (20 m)	

The Bluetooth word mark and logos are owned by the Bluetooth SIG, Inc. and any use of such marks by JK Audio, Inc. is under license.



© 2018, **JK Audio**, **Inc.** 1311 E. 6th St. Sandwich, IL. 60548 800.552.8346 • 815.786.2929 Se Habla Español jkaudio.com info@jkaudio.com



CE